



Powering Innovation



PROTECTION + AUTOMATION + CONTROL

AUXILIARY RELAY WITH 4 PAIRS OF S/R CONTACTS
TWO ELEMENT RELAY
JRV151x2

JVS ELECTRONICS PVT. LTD.

#121, Manchanayakanahalli,
Bangalore Mysore Highway, Bidadi,
Ramanagara District - 562 109, Karnataka, India
+91 94808 26272, +91 94808 26260
bangalore@jvselectronics.in, www.jvselectronics.in

AUXILIARY RELAY WITH 4 PAIRS OF S/R CONTACTS TWO ELEMENT RELAY JRV151x2

FEATURES

- ◆ Electromechanical design
- ◆ Plug-in construction
- ◆ Standardised contact arrangement
- ◆ Self or hand reset contacts
- ◆ Protective transparent cover for the element
- ◆ Compact panel mounting case

APPLICATION

Switching functions in protection and control circuits contact multiplication.



DESCRIPTION

The auxiliary relays are electromechanical, attracted armature type, used in control and alarm circuits. These relays are designed as plug-in elements with the plug-in base having 14 terminals & 4CO per element. Each element is enclosed in a dust proof moulded, transparent, polycarbonate cover. There is no hard wiring between the relay element and the rear terminals on the base. This results in a compact rugged and reliable design. Radio metal is used for the magnetic components such as the armature, the core and the yoke of the auxiliary relay to ensure good electrical performance. The contacts are made from phosphor bronze and are nickel plated. The contact tips are of pure silver. The use of these materials ensures very good contact

Auxiliary relays are available in the following versions

Contact and flag arrangement	Relay type
S/R contact and S/R or H/R or no flag or reverse flag	JRV 151x2

TECHNICAL DATA

RATINGS

Rated voltage	:	24,30, 48,110,220 V DC or 63.5, 110 or 230v, 50Hz AC
Operating range	:	75-120% of rated voltage for DC relays
	:	75-120% of rated voltage for DC relays
Reset value	:	Above 10% of the rated voltage
Burden	:	4 watts (maximum) at rated voltage Less
Operating time	:	than 20 ms at rated voltage(nominal) less
Reset time	:	than 10 ms
Operation indicator	:	a) self reset flag or b) hand reset flag or c) hand reset reverse flag for AC/DC fail indication or d) no flag

CONTACTS RATINGS

- Make & Carry continuous (AC - DC) : 2500 VA with maxima of 5 A and maxima of 660VAC
2500 W with maxima of 5A and maxima of 660VDC
- Make & Carry for 3s (AC - DC) : 7500 VA with maxima of 30 A and maxima of 660VAC
7500 W with maxima of 30A and maxima of 660VDC
- Break (AC-DC) : 2500VA with maxima of 5 A and maxima of 660VAC
: 100W (resistive) 50W (inductive) with maxima of 5A
and maxima of 250V DC
- Insulation : 1) 2 KV RMS, 50Hz. For 1 minute / 2.5 KV for 1s. Between
all terminals and case as per IEC 60255
2) 1 KV RMS, 50Hz. For 1 minute across open contacts as
per IEC 60255
- Operating temperature : -10 deg. To +55 deg.C

MECHANICAL DESIGN

Case dimensions in mm			
Relay type	front face dimensions width X Height in Sq. mm	Panel cutout dimensions width X Height in mm Tolerance +1 / -0	Depth in mm
Two element relay	96	92x92	115

TERMINAL DIAGRAM

- Note : Wiring diagram of relay types are given on request

ORDERING INFORMATION

- Relay type : Two element relay JRV 151x2
- Rated voltage : 24/30/48/50/110/220 VDC 63.5/110/230